



## D 10 PROXIMITY CARD READER

Makim D 10 proximity is a card reader with communication option of TCP/IP and is suitable for applications for indoor with its stylish case.



Makim D 10 Proximity Card Reader is used for access control applications with its 30.000 user capacity and stylish design. It works with card and password, with its 50.000 log capacity and it has door-turnstile opening function via relay (dry contact). D 10 provides fast operation with a reading speed under 20ms for 30.000 user.

TCP/IP communication provides access to all log information, entry-exit data, employee-based authorization, and all reports like daily, weekly and monthly reporting. Through USB connection, log data can be downloaded from the device. D 10 can also be connected to panel through wiegand in/ out.

The device works with 12 V power and it gives sound alarm with its built-in buzzer in every transaction. With all these features, D 10 Proximity Card Reader is suitable for not only small business centers, accommodation places or buildings but it also suitable for big factories, storage rooms, banks, prisons and similar industrial and commercial locations.

Card Capacity	30.000
Log Capacity	50.000
Card	Proximity
Communication	TCP/IP, USB, Wiegand In/Out
Relay	Yes, Dry Contact
Bell	Yes
Password	Yes
Language	Turkish
Operation Speed	High
Operation Voltage	12 V DC

## FACTORY

Address: Sincan Organize Sanayi Bölgesi, Erkunt Cd. No: 20 06930 Sincan / Ankara Phone: +90 (312) 267 56 87 Fax: 0 (312) 267 56 99 satis@makim.com.tr ANKARA SALES OFFICE Address: Batı Sitesi Mah. Gersan, 2307 Sk/3.Cad. No:16 06970 Ergazi / Ankara Phone: +90 (312) 257 02 52 Fax: 0 (312) 257 02 55 pazarlama@makim.com.tr BRANCH Address: Perpa Ticaret Merkezi, B Blok Kat: 7-8 No: 987-989 Şişli İstanbul Phone: +90 (212) 210 29 41 Fax: 0 (212) 210 68 15 sube@makim.com.tr WAREHOUSE AND TEHCNICAL DELIVERY Adres: Perpa Ticaret Merkezi, B Blok Kat: 1-2 No:57 Şişli İstanbul Phone: +90 (212) 210 29 41 Fax: 0 (212) 210 68 15 sube@makim.com.tr

## www.makim.com.tr